

# Product datasheet

Specifications



## TeSys D contactor - 3P(3 NO) - AC-3 - <= 440 V 65 A - 380 V AC 50/60 Hz coil

LC1D65AQ7

### Main

Range	TeSys TeSys Deca
Range of product	TeSys Deca
Product or component type	Contactors
Device short name	LC1D
contactor application	Motor control Resistive load
Utilisation category	AC-4 AC-1 AC-3 AC-3e
poles description	3P
[Ue] rated operational voltage	Power circuit: <= 690 V AC 25...400 Hz Power circuit: <= 300 V DC
[Ie] rated operational current	80 A (at <60 °C) at <= 440 V AC AC-1 for power circuit 65 A (at <60 °C) at <= 440 V AC AC-3 for power circuit 65 A (at <60 °C) at <= 440 V AC AC-3e for power circuit
[Uc] control circuit voltage	380 V AC 50/60 Hz

### Complementary

Motor power kW	11 kW at 400 V AC 50/60 Hz (AC-4) 18.5 kW at 220...230 V AC 50/60 Hz (AC-3) 30 kW at 380...400 V AC 50/60 Hz (AC-3) 37 kW at 500 V AC 50/60 Hz (AC-3) 37 kW at 660...690 V AC 50/60 Hz (AC-3) 18.5 kW at 220...230 V AC 50/60 Hz (AC-3e) 30 kW at 380...400 V AC 50/60 Hz (AC-3e) 37 kW at 500 V AC 50/60 Hz (AC-3e) 37 kW at 660...690 V AC 50/60 Hz (AC-3e)
Motor power hp	40 hp at 460/480 V AC 50/60 Hz for 3 phases motors 5 hp at 115 V AC 50/60 Hz for 1 phase motors 10 hp at 230/240 V AC 50/60 Hz for 1 phase motors 20 hp at 200/208 V AC 50/60 Hz for 3 phases motors 20 hp at 230/240 V AC 50/60 Hz for 3 phases motors 50 hp at 575/600 V AC 50/60 Hz for 3 phases motors
Compatibility code	LC1D
Pole contact composition	3 NO
Protective cover	With
[Ith] conventional free air thermal current	10 A (at 60 °C) for signalling circuit 80 A (at 60 °C) for power circuit
Irms rated making capacity	140 A AC for signalling circuit conforming to IEC 60947-5-1 250 A DC for signalling circuit conforming to IEC 60947-5-1 1000 A at 440 V for power circuit conforming to IEC 60947

<b>Rated breaking capacity</b>	1000 A at 440 V for power circuit conforming to IEC 60947
<b>[Icw] rated short-time withstand current</b>	640 A 40 °C - 10 s for power circuit 900 A 40 °C - 1 s for power circuit 110 A 40 °C - 10 min for power circuit 260 A 40 °C - 1 min for power circuit 100 A - 1 s for signalling circuit 120 A - 500 ms for signalling circuit 140 A - 100 ms for signalling circuit
<b>Associated fuse rating</b>	10 A gG for signalling circuit conforming to IEC 60947-5-1 125 A gG at <= 690 V coordination type 1 for power circuit 125 A gG at <= 690 V coordination type 2 for power circuit
<b>Average impedance</b>	1.5 mOhm - Ith 80 A 50 Hz for power circuit
<b>Power dissipation per pole</b>	9.6 W AC-1 6.3 W AC-3 6.3 W AC-3e
<b>[Ui] rated insulation voltage</b>	Power circuit: 600 V CSA certified Power circuit: 600 V UL certified Signalling circuit: 690 V conforming to IEC 60947-1 Signalling circuit: 600 V CSA certified Signalling circuit: 600 V UL certified Power circuit: 690 V conforming to IEC 60947-4-1
<b>Overvoltage category</b>	III
<b>Pollution degree</b>	3
<b>[Uimp] rated impulse withstand voltage</b>	6 kV conforming to IEC 60947
<b>Safety reliability level</b>	B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO 13849-1
<b>Mechanical durability</b>	6 Mcycles
<b>Electrical durability</b>	1.4 Mcycles 80 A AC-1 at Ue <= 440 V 1.45 Mcycles 65 A AC-3 at Ue <= 440 V 1.45 Mcycles 65 A AC-3e at Ue <= 440 V
<b>Control circuit type</b>	AC at 50/60 Hz
<b>Coil technology</b>	Without built-in suppressor module
<b>Control circuit voltage limits</b>	0.3...0.6 Uc (-40...70 °C):drop-out AC 50/60 Hz 0.8...1.1 Uc (-40...60 °C):operational AC 50 Hz 0.85...1.1 Uc (-40...60 °C):operational AC 60 Hz 1...1.1 Uc (60...70 °C):operational AC 50/60 Hz
<b>Inrush power in VA</b>	140 VA 60 Hz cos phi 0.75 (at 20 °C) 160 VA 50 Hz cos phi 0.75 (at 20 °C)
<b>Hold-in power consumption in VA</b>	13 VA 60 Hz cos phi 0.3 (at 20 °C) 15 VA 50 Hz cos phi 0.3 (at 20 °C)
<b>Heat dissipation</b>	4...5 W at 50/60 Hz
<b>Operating time</b>	4...19 ms opening 12...26 ms closing
<b>Maximum operating rate</b>	3600 cyc/h 60 °C
<b>Maximum operating rate</b>	3600 cyc/h at 60 °C

<b>Connections - terminals</b>	<p>Control circuit: screw clamp terminals 2 1...2.5 mm<sup>2</sup> - cable stiffness: flexible with cable end</p> <p>Control circuit: screw clamp terminals 1 1...4 mm<sup>2</sup> - cable stiffness: flexible without cable end</p> <p>Control circuit: screw clamp terminals 2 1...4 mm<sup>2</sup> - cable stiffness: flexible without cable end</p> <p>Control circuit: screw clamp terminals 1 1...4 mm<sup>2</sup> - cable stiffness: flexible with cable end</p> <p>Control circuit: screw clamp terminals 1 1...4 mm<sup>2</sup> - cable stiffness: solid without cable end</p> <p>Control circuit: screw clamp terminals 2 1...4 mm<sup>2</sup> - cable stiffness: solid without cable end</p> <p>Power circuit: EverLink BTR screw connectors 1 1...35 mm<sup>2</sup> - cable stiffness: flexible without cable end</p> <p>Power circuit: EverLink BTR screw connectors 2 1...25 mm<sup>2</sup> ♦♦ - cable stiffness: flexible without cable end</p> <p>Power circuit: EverLink BTR screw connectors 1 1...35 mm<sup>2</sup> - cable stiffness: flexible with cable end</p> <p>Power circuit: EverLink BTR screw connectors 2 1...25 mm<sup>2</sup> - cable stiffness: flexible with cable end</p> <p>Power circuit: EverLink BTR screw connectors 1 1...35 mm<sup>2</sup> - cable stiffness: solid without cable end</p> <p>Power circuit: EverLink BTR screw connectors 2 1...25 mm<sup>2</sup> - cable stiffness: solid without cable end</p>
--------------------------------	--

<b>Tightening torque</b>	<p>Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver flat Ø 6 mm</p> <p>Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver Philips No 2</p> <p>Power circuit: 8 N.m - on EverLink BTR screw connectors - cable 25...35 mm<sup>2</sup> hexagonal screw head 4 mm</p> <p>Power circuit: 5 N.m - on EverLink BTR screw connectors - cable 1...25 mm<sup>2</sup> hexagonal screw head 4 mm</p> <p>Control circuit: 1.7 N.m - on EverLink BTR screw connectors - with screwdriver pozidriv No 2</p> <p>Power circuit: 2.5 N.m - on EverLink BTR screw connectors - with screwdriver pozidriv No 2</p>
--------------------------	---

<b>Auxiliary contact composition</b>	1 NO + 1 NC
--------------------------------------	-------------

<b>Auxiliary contacts type</b>	<p>type mechanically linked 1 NO + 1 NC conforming to IEC 60947-5-1</p> <p>type mirror contact 1 NC conforming to IEC 60947-4-1</p>
--------------------------------	---

<b>Signalling circuit frequency</b>	25...400 Hz
-------------------------------------	-------------

<b>Minimum switching voltage</b>	17 V for signalling circuit
----------------------------------	-----------------------------

<b>Minimum switching current</b>	5 mA for signalling circuit
----------------------------------	-----------------------------

<b>Insulation resistance</b>	> 10 MOhm for signalling circuit
------------------------------	----------------------------------

<b>Non-overlap time</b>	<p>1.5 ms on de-energisation between NC and NO contact</p> <p>1.5 ms on energisation between NC and NO contact</p>
-------------------------	--

<b>mounting support</b>	<p>Rail</p> <p>Plate</p>
-------------------------	--------------------------

## Environment

<b>Standards</b>	<p>EN 60947-4-1</p> <p>EN 60947-5-1</p> <p>IEC 60947-4-1</p> <p>IEC 60947-5-1</p> <p>CSA C22.2 No 14</p> <p>UL 60947-4-1</p> <p>IEC 60335-2-40:Annex JJ</p> <p>UL 60335-2-40:Annex JJ</p> <p>IEC 60335-1:Clause 30.2</p>
------------------	--

<b>product certifications</b>	<p>CCC</p> <p>UL</p> <p>CB Scheme</p> <p>CSA</p> <p>CE</p> <p>UKCA</p> <p>Marine</p> <p>EAC</p>
-------------------------------	---

<b>IP degree of protection</b>	IP20 front face conforming to IEC 60529
<b>Protective treatment</b>	TH conforming to IEC 60068-2-30
<b>Climatic withstand</b>	conforming to IACS E10 exposure to damp heat conforming to IEC 60947-1 Annex Q category D exposure to damp heat
<b>Permissible ambient air temperature around the device</b>	-40...60 °C 60...70 °C with derating
<b>Operating altitude</b>	0...3000 m
<b>Fire resistance</b>	850 °C conforming to IEC 60695-2-1
<b>Flame retardance</b>	V1 conforming to UL 94
<b>Mechanical robustness</b>	Vibrations contactor open (2 Gn, 5...300 Hz) Vibrations contactor closed (4 Gn, 5...300 Hz) Shocks contactor closed (15 Gn for 11 ms) Shocks contactor open (10 Gn for 11 ms)
<b>Height</b>	122 mm
<b>Width</b>	55 mm
<b>Depth</b>	120 mm
<b>Net weight</b>	0.86 kg

## Packing Units

<b>Unit Type of Package 1</b>	PCE
<b>Number of Units in Package 1</b>	1
<b>Package 1 Height</b>	6.400 cm
<b>Package 1 Width</b>	13.900 cm
<b>Package 1 Length</b>	15.500 cm
<b>Package 1 Weight</b>	908.000 g
<b>Unit Type of Package 2</b>	S02
<b>Number of Units in Package 2</b>	10
<b>Package 2 Height</b>	15.000 cm
<b>Package 2 Width</b>	30.000 cm
<b>Package 2 Length</b>	40.000 cm
<b>Package 2 Weight</b>	9.365 kg

## Contractual warranty

<b>Warranty</b>	12 months
-----------------	-----------

## Sustainability

**Green Premium™ label** is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product's sustainability >](#)



Transparency RoHS/REACH

## Well-being performance

✓ Reach Free Of Svhc

✓ Toxic Heavy Metal Free

✓ Mercury Free

✓ Rohs Exemption Information [Yes](#)

✓ Pvc Free

## Certifications & Standards

**Reach Regulation** [REACH Declaration](#)

**Eu Rohs Directive** Compliant  
[EU RoHS Declaration](#)

**China Rohs Regulation** [China RoHS declaration](#)  
Pro-active China RoHS declaration (out of China RoHS legal scope)

**Environmental Disclosure** [Product Environmental Profile](#)

**Weee** The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

**Circularity Profile** [End of Life Information](#)